


SWS-15D2
SWS-15D4





SWS-12D2
SWS-12D4





SWS-10D2
SWS-10D4





ALPINE®

ALPINE ELECTRONICSMARKETING,INC.
1-7 Yukigaya-otsukamachi,
Ota-ku, Tokyo 145-0067, Japan
Tel: (03) 5499-4531

ALPINE ELECTRONICS OF AMERICA, INC.
19145 Gramercy Place, Torrance,
California 90501, U.S.A.
Tel: 1-800-ALPINE-1 (1-800-257-4631)

ALPINE ELECTRONICS OF CANADA, INC.
777 Supertest Road, Toronto,
Ontario M3J 2M9, Canada
Tel: (416) 736-6211

ALPINE ELECTRONICS OF AUSTRALIA PTY. LTD.
161-165 Princes Highway, Hallam
Victoria 3803, Australia
Tel: (03) 8787-1200

ALPINE ELECTRONICS DE ESPAÑA, S.A.
Portal de Gamarra 36, Pabellón 32
01013 Vitoria (Álava). APDO. 133, Spain
Tel: (945) 283-588

ALPINE ELECTRONICS GmbH
Wilhelm-Wagenfele-Straße 1-3
80807 München, Germany
Tel: (089) 324-2640

ALPINE ELECTRONICS (Benelux) GmbH
Leuvensesteenweg 510-B6
1930 Zaventem, Belgium
Tel: 02-7251315

ALPINE ELECTRONICS OF U.K., LTD.
Alpine House Earlplace Business Park,
Fletchamstead Highway, Coventry CV4, 9TW
United Kingdom
Tel: (2476) 719-500

ALPINE ELECTRONICS FRANCE S.A.R.L.
98,Rue de la Belle Etoile, Z.I. Paris Nord,
B.P. 50016, 95945, Roissy Charles de Gaulle
Cédex, France
Tel: (01) 4863-8989

ALPINE ITALIA S.p.A.
Viale C. Colombo 8,
20090 Trezzano Sul Naviglio (MI), Italy
Tel: (02) 484-781

Printed in CHINA



TYPE-S SUBWOOFER
HAUT-PARLEUR D'EXTRÊMES GRAVES TYPE-S
APPLICATION GUIDE
GUIDE D' APPLICATION

SWS-15D4

15 Inch Dual Voice Coil Subwoofer (4Ω)+(4Ω)
Haut-parleur d'extrêmes graves à double bobine 15 po (4Ω)+(4Ω)

SWS-15D2

15 Inch Dual Voice Coil Subwoofer (2Ω)+(2Ω)
Haut-parleur d'extrêmes graves à double bobine 15 po (2Ω)+(2Ω)

SWS-12D4

12 Inch Dual Voice Coil Subwoofer (4Ω)+(4Ω)
Haut-parleur d'extrêmes graves à double bobine 12 po (4Ω)+(4Ω)

SWS-12D2

12 Inch Dual Voice Coil Subwoofer (2Ω)+(2Ω)
Haut-parleur d'extrêmes graves à double bobine 12 po (2Ω)+(2Ω)

SWS-10D4


10 Inch Dual Voice Coil Subwoofer (4Ω)+(4Ω)
Haut-parleur d'extrêmes graves à double bobine 10 po (4Ω)+(4Ω)


SWS-10D2

10 Inch Dual Voice Coil Subwoofer (2Ω)+(2Ω)
Haut-parleur d'extrêmes graves à double bobine 10 po (2Ω)+(2Ω)

			Type-S					
			SWS-10D2	SWS-10D4	SWS-12D2	SWS-12D4	SWS-15D2	SWS-15D4
General Specifications			2Ω+2Ω	4Ω+4Ω	2Ω+2Ω	4Ω+4Ω	2Ω+2Ω	4Ω+4Ω
Sealed	Taille		10"		12"		15"	
Frequency Response	Response en Fréquence		28Hz-200Hz		26Hz-200Hz		24Hz-200Hz	
Power Range	Plage de Puissance		150W-500W RMS (efficace)					
Power Handling	Puisance Admissible		500W RMS (efficace) / 1500W PEAK (de crête)					
Magnet Weight	Poids de l'aimant		64 oz		64 oz		106 oz	
Voice Coil Diameter	Diamètre de la bobine		65.5 mm (2.6")					
Thiel-Small Parameters								
Sensitivity (1W/1m)	Sensibilité (1W/1m)	*SPL*	85.1dB	85.5 dB	86.4 dB	86.5 dB	88.5 dB	88.7 dB
DC Resistance	Résistance CC	*Re*	1.8Ω+1.8Ω	3.5Ω+3.5Ω	1.8Ω+1.8Ω	3.5Ω+3.5Ω	1.8Ω+1.8Ω	3.5Ω+3.5Ω
Inductance	Inductance	*Le*	1.87 mH	4.84 mH	1.87 mH	4.84 mH	1.87 mH	4.84 mH
Free Air Resonance	Résonance à l'air libre	*Fs*	35 Hz		34 Hz		27 Hz	
Equivalent Stiffness	Raiduer équivalente	*Vas*	25 L		44 L		107 L	
Mechanical Q	Q Méchanique	*Qms*	7.54	8.65	8.37	9.43	7.69	8.57
Electrical Q	Q Électrique	*Qes*	0.52	0.49	0.66	0.6	0.51	0.46
Total Q	Q Total	*Qts*	0.49	0.46	0.61	0.57	0.48	0.44
Cone Area	Surface du diaphragme	*Sd*	333 cm^2		479 cm^2		779 cm^2	
Linear Excursion	Displacement Lineáre	Xmax (1-way)	15 mm					
Mechanical Travel	Déplacement Mécanique	Xmech (P-P)	64 mm		64 mm		68 mm	

Note: Specifications subject to change without notice






2Ω + 2Ω


SWS-10D4 / SWS-12D4 / SWS-15D4
SWS-10D2 / SWS-12D2 / SWS-15D2

Example 2 One Amplifier + One Subwoofer




Caution ! Consult amplifier owner's manual for 1Ω connection.
Attention : lire le manuel de l'amplificateur pour la connexion à 1Ω .


Example 4 Two Amplifiers + One Subwoofer



Example 6 One Amplifier and Two Subwoofers



Example 8 One Amplifier + Four Subwoofers



		SWS-10D2/D4	SWS-12D2/D4	SWS-15D2/D4
Sealed Box Range	Net Internal Volume	0.5-0.85 ft^3	0.65-1.0 ft^3	1.25-2.0 ft^3
Recommened Sealed Box	External Box Dimensions	12"x12"x10"	14"x14"x11.5"	16"x16"x12.5"
	Gross Internal Volume	0.54 ft^3	0.90 ft^3	1.34 ft^3
	Net Internal Volume	0.50 ft^3	0.85 ft^3	1.27 ft^3
	F3, Qtc	D2: 54 Hz, 0.78 D4: 54 Hz, 0.73	D2: 47 Hz, 0.96 D4: 49 Hz, 0.91	D2: 46 Hz, 0.91 D4: 48 Hz, 0.83
Vented Box Range	Net Internal Volume	0.75-1.3 ft^3	1.0-1.5 ft^3	2.0-3.0 ft^3
	Tuning	35-39Hz	32-37Hz	28-32Hz
Recommened Vented Box	External Box Dimensions	21.5"x12"x11.5"	22.5"x12.5"x14"	25"x15.5"x17.5"
	Gross Internal Volume	1.22 ft^3	1.67 ft^3	3.05 ft^3
	Vent Area (dimensions)	10in^2 (10"x 1")	12.5in^2 (12.5"x 1")	20in^2 (16"x 1.25")
	Vent length	18"	18"	21"
	Vent Displacement	0.18 ft^3	0.22 ft^3	0.38 ft^3
	Net Internal Volume (Vb)	1.0 ft^3	1.4 ft^3	2.6 ft^3
	F3, ripple, Fb	D2: 32Hz, 3.1dB, 38Hz D4: 32Hz, 2.5dB, 38Hz	D2: 32Hz, 4.4dB, 36Hz D4: 31Hz, 4.1dB, 36Hz	D2: 29Hz, 3.1dB, 31Hz D4: 29Hz, 2.6dB, 31Hz

Notes:
1) Recommended enclosure net Internal volume is based upon 3/4" (19mm) MDF enclosure construction.
2) Consult the table below for alternative enclosure net internal volume calculation.

Front Mount Displacement* (magnet in)	-0.04 ft^3	-0.06 ft^3	-0.07 ft^3
Reverse Mount Added Volume* (magnet out)	+0.06 ft^3	+0.08 ft^3	+0.15 ft^3


***Based upon 3/4" (19mm) baffle thickness, with opening cut approximately to gasket inner diameter**

		SWS-10D2/D4	SWS-12D2/D4	SWS-15D2/D4
Gamme Box Sealed	Net volume interne	0.5-0.85 pi^3	0.65-1.0 pi^3	1.25-2.0 pi^3
recommened Boîte Scellé	Dimensions extérieures	12 po x12 po x10 po	14 po x14 po x11.5 po	16 po x16 po x12.5 po
	Volume intérieur brut	0.54 pi^3	0.90 pi^3	1.34 pi^3
	Volume intérieur Net ***	0.50 pi^3	0.85 pi^3	1.27 pi^3
	F3, Qtc	D2: 54 Hz, 0.78 D4: 54 Hz, 0.73	D2: 47 Hz, 0.96 D4: 49 Hz, 0.91	D2: 46 Hz, 0.91 D4: 48 Hz, 0.83
Gamme charge bass-reflex	Volume net interne	0.75-1.3 pi^3	1.0-1.5 pi^3	2.0-3.0 pi^3
	mise au point	35-39Hz	32-37Hz	28-32Hz
recommened charge bass-reflex	Dimensions extérieures	21.5 po x12 po x11.5 po	22.5 po x12.5 po x14 po	25 po x15.5 po x17.5 po
	Volume intérieur brut	1.22 pi^3	1.67 pi^3	3.05 pi^3
	Aire de l'évent (dimensions)	10in^2 (10 po x 1 po)	12.5in^2 (12.5 po x 1 po)	20in^2 (16 po x 1.25 po)
	Longueur de l'évent	18"	18"	21"
	déplacement de l'évent	0.18 pi^3	0.22 pi^3	0.38 pi^3
	Volume intérieur Net (Vb)***	1.0 pi^3	1.4 pi^3	2.6 pi^3
	F3, crête, Fb	D2: 32Hz, 3.1dB, 38Hz D4: 32Hz, 2.5dB, 38Hz	D2: 32Hz, 4.4dB, 36Hz D4: 31Hz, 4.1dB, 36Hz	D2: 29Hz, 3.1dB, 31Hz D4: 29Hz, 2.6dB, 31Hz

Notes:
1) Recommandé enceinte volume net inteme est basée sur 3/4 "(19mm) de construction boîtier en MDF.
2) Consulter le tableau ci-dessous pour le calcul de filet d'enclos altemative volume interne.

Avant le déplacement du Mont * (aimant)	-0.04 ft^3	-0.06 ft^3	-0.07 ft^3
Inverser Volume mont Ajouté * (des aimants)	+0.06 ft^3	+0.08 ft^3	+0.15 ft^3

*** Sur la base de l'épaisseur du déflecteur 3/4" (19mm), avec une ouverture coupée à peu près à joint diamètre intérieur**


Reinforced Parabolic Cone Structure with
Poly-Mica Dust Cap & Pulp-Kevlar Cone Body
High Amplitude Multi-Roll
Santoprene® Surround
(Patent Pending)
Concealed
Mount Gasket
(Integrated Grille System
Ready, US Pat #7,760,900)
High Strength
Steel Frame
Progressive Conex® Spider
with Reinforced Layer
Tinsel Leads (US Pat #6,810,988)
Perimeter Venting with
Airflow Management
System (US Pat #7,684,585)
8AWG Push Terminals with
VC Configuration Jumpers
High-Excursion Underhung
Voice Coil Configuration
High-Grade Strontium
Ferrite Magnets
Compound Radius Curve
Extended Pole Geometry
(US Pat #6,639,993)
Dual Flare Pole Vent with
Airflow Back Plate
65mm Voice coil with High-Temp DVC Winding on
Spiral Cut Aluminum former (D4 = 6-layer, D2 = Split 5-Layer)